

T&J ELECTRIC (SINGAPORE) PTE LTD

Company Registration No: 200205797Z
10 Ubi Crescent, #02-24, Ubi Techpark, Singapore 408564
Telephone: +65 6547-4333 Fax: +65 6547-4666

Date: 4/12/2017

Subject: Product Info: W2710 + W2743 + K1201 DMB
("Do not Disturb", "Make up Room" Indicator & Bell Switch)
TM-020049.2

Overview:

- "Do not disturb" and "Make-up room" Indicator with Bell Switch which is installed outside hotel guest room.
- RED Indicator – "Do Not Disturb"
GREEN Indicator – "Make-up room"
- It works with a "Do Not Disturb" and "Make-up room" switch (e.g. K2772L-2) inside the hotel guest room to form a complete circuit.

Technical Data:

Frame: K1201

- Product Range: Radiance
All color code for Radiance is applicable on this product.
- Dimension: 86 * 86 mm
- Fix Center: 60.3 mm
- Fix Screws: M3.5 * 18 mm

Bell Switch module: W2710

- Product Range: Deco
All color code for Deco is applicable on this product.
- Dimension: 40*23 mm
- Rating: Voltage: 250V~
Current: 16A
- Recommended terminal wire gauge:
1.5mm²~2.5mm²

Front View



W2710+W2743+K1201

Back View



T&J ELECTRIC (SINGAPORE) PTE LTD

Company Registration No: 200205797Z
10 Ubi Crescent, #02-24, Ubi Techpark, Singapore 408564
Telephone: +65 6547-4333 Fax: +65 6547-4666

Date: 4/12/2017

Subject: Product Info: W2710 + W2743 + K1201 DMB
("Do not Disturb", "Make up Room" Indicator & Bell Switch)
TM-020049.2

Indicator Module: W2743

- Product Range: Deco
- Dimension: 40*23 mm
- Rating:
Voltage: 250V~
Current <2mA (LED Indicator current)
- Recommended terminal wire gauge:
0.5mm²~1.5mm²

Mounting/Wall Box:

- >35 mm depth

Product code Note:

For this combination:

K1201-MSL-D (Frame) + W2710-MSL/S47
(Bell switch) + W2743 (DND+MUR Indicator),
use customized product code:

ZCT-CUSTOM-MADE-627

T&J ELECTRIC (SINGAPORE) PTE LTD

Company Registration No: 200205797Z
10 Ubi Crescent, #02-24, Ubi Techpark, Singapore 408564
Telephone: +65 6547-4333 Fax: +65 6547-4666

Date: 4/12/2017

Subject: Product Info: W2710 + W2743 + K1201 DMB
("Do not Disturb", "Make up Room" Indicator & Bell Switch)
TM-020049.2

Sample interconnection diagram:

